

Play a sound or message when an alarm is triggered

12V
DC

200mA
CURRENT

10
INPUTS

TERMINAL

WALL
MOUNT



voiceoff.com



A loudspeaker unit that will play back messages when it receives an alarm input.

VoiceOFF
.com



MK3

VOX300

Key Features

- ✓ Up to 10 alarm inputs
- ✓ Powerful 10W output
- ✓ Sounds stored on SD card
- ✓ IP65 rated external use
- ✓ Download sounds or record your own
- ✓ Automatically triggered by alarm inputs
- ✓ Use as a talkback amp with DVRs
- ✓ Talk live with a microphone
- ✓ Stores 9999 pre-recorded sounds
- ✓ MP3 compatible

Description

The VoiceOff is an alarm activated voice or sound warning unit that has 10 separate alarm inputs to trigger up to 10 different sound recording files and with the new added feature of an RS485 or RS232 input can trigger up to 9999 sounds!!!

The unit even boasts a line-out connection so it can be used to talk back to a visitor or intruder in an area when used with a simple microphone. The alienDVR allows this function to be carried out remotely over the internet using its alienVision software. Imagine being able to warn off an intruder at your business when you're miles away, what would you say?

Housed in an IP65 ABS casing, the VoiceOff can be fitted in or outdoors and the volume is fully adjustable to suit the environment. Cabling is simple as the unit is low voltage 12V DC (200mA).

Works with: PIRs, Door Contacts, Panic buttons, Break beams, Push buttons & Pressure Pads.

Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright 2017

Play a sound or message when an alarm is triggered

12V
DC

200mA
CURRENT

10
INPUTS

TERMINAL

WALL
MOUNT



voiceoff.com



Pick a message or sound that fits your needs:

Welcome: Use the VoiceOff to promote your business, sound promotional messages when a customer enters an area of the store. "Welcome to Groves Garden Centre..."

Inform: Use with a PIR at a construction site to inform staff about risks in the area where health & safety is paramount. "hard hats must be worn in this area."

Deter: Use with a PIR to trigger a pre-recorded sound file of a police siren to scare off intruders. Great in areas that are prone to vandalism.

Warn: Use with a PIR or break beam to trigger a warning message when an intruder is detected. You may record your own messages! "Warning, intruder detected..."

Record your own messages or visit www.voiceoff.com to see our massive range of sounds and messages available to download.

How It Works



Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright 2017

Play a sound or message when an alarm is triggered

12V
DC

200mA
CURRENT

10
INPUTS


TERMINAL

WALL
MOUNT



voiceoff.com



What's In The Box



Voice Off Unit



Micro SD with Sound Files

Specification

Audio Output	8W 80Ohms
Power	12v DC
Alarm Inputs	10
Speaker	8W 8 ohms
Mount	Wall mount fixing lugs
Case	Ivory ABS Weatherproof IP65
Memory	Max SD Card 32Gb
Card Supplied	4GB SD card supplied
Dimensions	H234 x W188 x D85mm

Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright 2017

Installer Details :